

Finally worked the pegs out – they have a securing lug (right hand end in the photo) at the far, hidden end. Use a big flat blade screwdriver to rotate them if you need to. The lug is on the opposite side to the split that runs the length of the peg. Rock the legs backwards to take the pressure off the pegs and they come out fairly easily.



Final check that all wiring is free and you can unhook the springs and lower the tub gently to the ground. Then remove the springs from the tub and replace them loosely on the cabinet.

Remove the tub from the front of the machine and undo all the Torx screws holding the tub halves together.



These two cable ties need to be cut off. I added the tape both to identify the place for the wire to be secured, and to keep the wiring together. These ties have the tails cut off – I guess for a reason.

